M4*20mm Screw

Panel Mount Bracket

Panel
(8mm Max Thickness)

EVA Seal

M4*8mm Screw

11.606
[294.8]

8.378
[212.8]

Cutout dimension is 11.61"(294.8mm) by 8.38"(212.8mm).
Thickness of panel cannot exceed 8mm.

Place EVA Seal on the
back of monitor

Magnified View to the right:

Step 1: Create panel cut out, place EVA seal, and install two bottom brackets.

Install the longer M4*20 mm Screw
into the bracket.

Install the shorter M4x8 Screws
into the rear monitor enclosure.

Step 2: Place the monitor into the panel cutout.

Step 3: Install the four remaining brackets. One on the left,
One on the right, and two on top.

Step 4: Tighten the shorter M4x8mm screws to secure the
bracket and tighten the longer M4x20mm screws to
secure the monitor againtst the panel.

.126
[3.2]

.126
[3.2]